

# System Backup Procedure

Your valuable data is at risk if you do not perform regular backups. Epicor Eagle software can automatically backup your information every day.

## Objectives

- Backup Basics
- Creating a Shutdown Queue
- Backup Scheduling
- Confirm the Backup Status

## Backup Basics

Open *Network Access* and sign on to view the *Backup File Maintenance*. Type *MBC* and click *Enter*.

Backup schedules are typically based on a six or seven-day cycle, depending upon how many days a week your store is open.

If you perform a *Secure Data Backup* then the labels for each day will start with *SDB* and be followed by a number. *This* section shows the date of the last seven backup attempts, what time they were attempted, and whether they were successful.

If you perform *Tape Backup*, then the labels start with *BK* followed by a letter.

Eagle also offers a combination of both backups as you can see here. CDs, DVDs, and USB drives are automatically labeled. Tape sets are labeled when your system is installed. All forms of backup will be referred to as *media* in this course.

Media can be relabeled at any point by running *WLABEL* in *Network Access*. Running *RLABEL* identifies the current media's name. For more information about these procedures, refer to the *Eagle Online Help*.

## Creating a Shutdown Queue

To set up automated backup, you must create a *Shutdown Queue*. From the *Network Access Function* prompt, type *CEQ* and press *Enter*.

The *Create an End-of-Day Report Queue* screen displays. Enter the name of the Report Queue *here*.

Use the letters *SHUTDWN*. Notice there is no letter O. You can not use *SHUTDOWN* as that is the name of another program.

In the *Function Name* field, type *SHUTDOWN*.

In *Comment* lines, type a comment to identify this queue, such as "*CLOSING REPORT*".  
Click *Display*.

On the Shutdown Queue Settings page leave *these* options as is. Press the down arrow on your keyboard to reach *Backup Settings*.

In the *Label a non-backup tape?* field, Select *Y* if you want *BACKUP* to label a non-backup tape with the expected tape set and overwrite the original contents of the tape. Select *N* if you don't want *BACKUP* to overwrite the inserted tape if it is not a labeled backup tape.

In the *Re-label an Incorrect Backup Tape?* field, select *N* if you don't want *BACKUP* to re-label a backup tape that does not match the expected tape set.

Select *Y* if you want *BACKUP* to re-label the tape to the expected tape set. We recommend "*N*" so the labels on your tapes do not change.

Eagle will never overwrite the last successful backup. This preserves your data in case you left the media in from the previous day

Click *Add* to save your changes.

Click **END** to exit the program.

## Backup Scheduling

To schedule a backup, select *Systems Management*. Then select *Schedule End-of-Day Queue* or type *SEQ* in the *Launch Bar*. Select *Add* from the ribbon menu.

In the *Queue name* drop-down, choose *SHUTDWN*. Determine what time you want the backup to run by selecting the *Schedule Name*.

Click *OK*.

*SHUTDWN* is now listed on the *End-of-Day Queue*. Under the *Enable* column, select the value *Y* and click *OK*.

Click *Change* to save your update.

## Confirm the Backup Status

Storing the backup media in a different offsite location ensures redundancy.

Confirm that the backup was successful each morning and then Swap out the CD, tape, or USB.

If the previous day's backup was successful and not removed, the current day's backup will not run.

From the *Utilities* menu, select *Show Application/System Logs*. Here we see that last night's backup was updated.

You can also open the *Eagle Event Journal Viewer* and sort the Description field using the word "backup".

Another source of information is *MBC*. Success indicates that your backup was completed for the associated date.

## Recap

Backups are vital to ensure your stores' critical data is protected.

The contents of this document are for informational purposes only and are subject to change without notice. Epicor Software Corporation makes no guarantee, representations or warranties with regard to the enclosed information and specifically disclaims, to the full extent of the law, any applicable implied warranties, such as fitness for a particular purpose, merchantability, satisfactory quality or reasonable skill and care. This document and its contents, including the viewpoints, dates and functional content expressed herein are believed to be accurate as of its date of publication. The usage of any Epicor software shall be pursuant to the applicable end user license agreement and the performance of any consulting services by Epicor personnel shall be pursuant to applicable standard services terms and conditions. Usage of the solution(s) described in this document with other Epicor software or third party products may require the purchase of licenses for such other products. Epicor, the Epicor logo, and are trademarks of Epicor Software Corporation, registered in the United States and other countries. All other marks are owned by their respective owners. Copyright © 2021 Epicor Software Corporation. All rights reserved.

---

## About Epicor

Epicor Software Corporation drives business growth. We provide flexible, industry-specific software that is designed around the needs of our manufacturing, distribution, retail, and service industry customers. More than 40 years of experience with our customers' unique business processes and operational requirements is built into every solution—in the cloud, hosted, or on premises. With a deep understanding of your industry, Epicor solutions spur growth while managing complexity. The result is powerful solutions that free your resources so you can grow your business. For more information, [connect with Epicor](#) or visit [www.epicor.com](http://www.epicor.com).

# EPICOR

#### Corporate Office

804 Las Cimas Parkway  
Austin, TX 78746

USA

Toll Free: +1.888.448.2636

Direct: +1.512.328.2300

Fax: +1.512.278.5590

#### Latin America and Caribbean

Blvd. Antonio L. Rodriguez #1882 Int. 104

Plaza Central, Col. Santa Maria

Monterrey, Nuevo Leon, CP 64650

Mexico

Phone: +52.81.1551.7100

Fax: +52.81.1551.7117

#### Europe, Middle East and Africa

No. 1 The Arena

Downshire Way

Bracknell, Berkshire RG12 1PU

United Kingdom

Phone: +44.1344.468468

Fax: +44.1344.468010

#### Asia

238A Thomson Road #23-06

Novena Square Tower A

Singapore 307684

Singapore

Phone: +65.6333.8121

Fax: +65.6333.8131

#### Australia and New Zealand

Suite 2 Level 8,

100 Pacific Highway

North Sydney, NSW 2060

Australia

Phone: +61.2.9927.6200

Fax: +61.2.9927.6298